

Studio Auto Clam 28-38 Press

How to change a Probe

Replacement/Removal of a Probe

N.B. Before undertaking any work, switch off the power supply to the machine and unplug the machine from the electricity supply

1. Separate Electrical Box by unscrewing 4 screws (pic 1 & inset)
2. Lift the top half of Electrical Box upwards and pivot towards front of Press (pic 2)
3. With a screwdriver remove Probe wires (pic 2 arrow-a), Element wires (pic 2 arrow-b) and Earth wire (pic 2 arrow-c), taking note of the connections for future reference when reinstalling
4. Lift top half of Electrical Box up and allow it to hang down the back of the Press by attached wires
5. Using a 30 mm Spanner remove nut from Cable Gland and pull wires out from hole in Electrical Box (pic 3)
6. With a 14 mm Spanner remove bolt from Heat Plate (pic 4)
7. Remove screws securing Heat Plate Cover (pic 5)
8. Lift Heat Plate Cover from front and using a 32 mm Spanner, remove Hex bolt in an anticlockwise direction (pic 6)
9. Put Arm/Handle into the up position, leaving Heat Plate on Silicone Pad (pic 7)
10. Remove Heat Plate insulation material
11. Using a 10 mm Spanner, unlock the nut holding Probe in place (pic 8), then pull Probe wire out from sleeving

Re-installation of replacement Probe

1. Installation is a reversal of removal
- N.B.** When refitting Hex bolt into Heat Plate, apply a small amount of thread locking compound to the top of the nut

